



1 产品概述 Product Summarize

用于直流电路中。在保护或自动电路中,要作为电流动作和电压保持(ZJ1-1型)或电压动作和电流保持(ZJ1-2)。

电磁式阀型,壳体有板前接线、板后接线两种结构形式。

This series are applying for DC circuit in protective or automatic circuit as current operating and voltage holding (ZJ1-1 type) or voltage operating and current holding (ZJ1-2).

This series adopt electromagnetic valve type, and the shell has two wiring mode: front wiring and back wiring.

2 主要技术参数 Main Technological Parameter

型号 Type		ZJ1-1	ZJ1-2
额定值 Rated value	电压(V) Voltage (V)	220,110,48,24	
	电流(A) Current (A)	1,2,4	
动作值 Operating value	电压(V) Voltage (V)		$\leq 70\%U_n$
	电流(A) Current (A)	$\leq I_n$	
保持值 Holding value	电压(V) Voltage (V)	$\leq 70\%U_n$	
	电流(A) Current (A)		$\leq 80\%I_n$
返回值 Return value	电压(V) Voltage (V)		$\geq 35\%U_n$
	电流(A) Current (A)	$\geq 3\%I_n$	

3 安装开孔尺寸、接线图 Mounging plate opening size,Wiring drawing

